

Public Safety Antennas

Exclusive Flexi-Whip Magnetic Mount Antenna

Proven Durability Reduces Vehicle Downtime

- Doesn't break on impact. Bends and bounces back
- Field tunable from 136MHz to 1GHz
- Significantly reduces life cycle cost on fleet vehicles
- Retrofit existing NMO mounts
- Available in NMO roof-mount and magnet mount

| MODEL NUMBER | MGNT-FT-NITI | | |
|-------------------------|--|--------------|-----------|
| Frequency Range(MHz) | 136MHZ - 1GHz | | |
| Bandwidth (MHz) | 18 Mhz @ 136 | 90 MHz @ 450 | 150 @ 850 |
| SWR | <2:1 | | |
| Power Rating (watts) | 150 | | |
| Gain | Unity | | |
| Pattern | Omni-directional | | |
| Mast Material | Rubber coated Nitinol | | |
| Maximum Height | 23" @ 136MHz | | |
| Feed Line | 17 ft. RG-58/U | | |
| Connectors (choose one) | PL259, Mini UHF, BNC, TNC, SMA, N, QMA | | |

*MGNT-FT-NITI(Magnet Mount)
Also available in: ROOF-FT-NITI(Roof Mount)



(MGNT-FT-NITI)